


# Data Sheet

## Auto Ranging Tool Kit® DMM Model 2705B



The 2705B is a full-featured auto-ranging DMM that combines performance, value and functionality. The 3400 count LCD can display resistance values up to 40 MΩ. With the auto-power-off feature, you won't have to worry about accidental battery consumption. Value-packed features make this meter a must in every "Tool Kit".

### Features

- Magnetic hanger
- One-handed operation
- Auto/manual ranging
- Auto power off
- Measures up to 10 A (AC & DC)
- DC voltage to 1000 V
- AC voltage to 750 V
- Resistance to 40 MΩ
- Continuity test
- Diode test

## Specifications

model

2705B

2705B	
<b>DC Volts</b>	
Ranges	400 mV, 4 V, 40 V, 400 V, 1000V
Resolution	0.1 mV, 1 mV, 10 mV, 100 mV, 1 V
Accuracy	±(1.0 % rdg + 2 dgts)
Input Impedance	400 mV: >100 MΩ; 4 V: 10 MΩ; 40 V to 1000 V: 9.1 MΩ
Overload Protection	1000 VDC or 750 VACrms
<b>AC Volts (50 Hz-500 Hz)</b>	
Ranges	400 mV, 4 V, 40 V, 400 V, 750V
Resolution	0.1 mV, 1 mV, 10 mV, 100 mV, 1 V
Accuracy	50 Hz to 100 Hz ±(2.0 % rdg + 5 dgts)
Input Impedance	400 mV: >100 MΩ; 4 V: 10 MΩ; 40 V to 750 V: 9.1 MΩ
Overload Protection	1000 VDC or 750 VACrms
<b>DC Current</b>	
Ranges	400 uA, 4000 uA, 40 mA, 400 mA, 10 A
Resolution	0.1 uA, 1 uA, 10 uA, 100 uA, 10 mA
Accuracy	400 uA to 400 mA ranges: ±(2.0 % rdg + 2 dgts) 10 A range: ±(3.0 % rdg + 3 dgts)
Input Protection	0.5 A/500 V & 10 A/600 V fast blow ceramic fuses
10A Input	10 A for 60 sec max. followed by a 10 minute cooling period
<b>AC Current (50 Hz-500 Hz)</b>	
Ranges	400 uA, 4000 uA, 40 mA, 400 mA, 10 A
Resolution	0.1 uA, 1 uA, 10 uA, 100 uA, 10 mA
Accuracy	400 uA to 400 mA ranges: ±(2.5 % rdg + 5 dgts) 10 A range: ±(3.5 % rdg + 5 dgts)
Input Protection	0.5 A/500 V & 10 A/600 V fast blow ceramic fuses
10A Input	10 A for 60 sec max. followed by a 10 minute cooling period
<b>Resistance</b>	
Ranges	400 Ω, 4 kΩ, 40 kΩ, 400 kΩ, 40 MΩ
Resolution	0.1 Ω, 1.0 Ω, 10 Ω, 100 Ω, 10 kΩ,
Accuracy	400 Ω to 400 kΩ ranges: ±(1.5 % rdg + 4 dgts) 4 MΩ range: ±(2.5 % rdg + 4 dgts) 40 MΩ range: ±(5.0 % rdg + 4 dgts)
Open Circuit Voltage (typical)	-0.45 VDC (-1.2 VDC on 400 Ω range)
Overload Protection	500 VDC/ACrms
<b>Diode Test</b>	
Test Current	1.0 mA (typical)
Resolution	10 mV
Accuracy	±(3.0 % rdg + 3 dgts)
Audible Indication	<0.25 V
Open Circuit Voltage	3.0 VDC (typical)
Overload Protection	500 VDC/ACrms
<b>Continuity</b>	
Audible Indication	Less than 25 Ω
Response Time	500 ms
Overload Protection	500 VDC/ACrms
<b>General</b>	
Display	3 3/4 digit, 4000 count LCD
Polarity	Automatic, positive implied, negative polarity indication
Overrange	OL or -OL is displayed
Low Battery Indication	Battery symbol will display when battery voltage drops below operating levels
Measurement Rate	2 times per second
Auto Power Off	Approximately 10 minutes
Operating Environment	0°C to 50°C at <70 % relative humidity
Storage Environment	-20°C to 60°C at 0 to 80 % relative humidity
Accuracies	Stated accuracy at 23°C ±5°C at <75 % relative humidity
Temperature Coefficient	0.1 x (specified accuracy) per °C. (°C to 18°C, 28°C to 50°C)
Power	Single standard 9 volt battery, NEDA 1604, JIS 006P, IEC 6F22
Battery Life	200 hours typical
Dimensions	165 mm (H) x 78 mm (W) x 42.5 mm (D)
Weight	Approximately 10 oz. (285 g) with battery and hanger

**Three-Year Warranty**

Supplied Accessories: User manual, one set of test leads, one spare fuse, and 9V battery (installed)

# B&K Precision's 2700 Tool Kit® Series

## Models 2703C, 2704C, 2705B, 2706B, 2707B, 2708B, 2709B & 2712

These excellent meters are for most jobs that require flexibility, accuracy and speed. Value-packed features make these meters a must for everyone's "Tool Kit®".

Common Features:

- DC Voltage to 1000V
- DC Current to 10A
- Diode test
- Magnetic hanging strap
- AC Voltage to 750V
- Continuity test
- Drop resistant case



**Magnetic Hanging Strap**

This convenient feature allows you to hang your DMM on any magnetic metallic surface freeing up your hands for troubleshooting.

**Back Light / Easy-to-Read LCD**

Model 2706B


Ultra-bright blue LCD back light for low ambient light measurements

Models 2709B & 2712

Large easy-to-read LCD with green LED backlight

### Single-handed operation

The ergonomic design allows both left and right handed users to rotate the knob while holding the meter in one hand. While one hand keeps the probe on the circuit, the other hand changes the meter's function. This speeds up troubleshooting because you don't have to locate the probe point in the circuit again.



Features	models							
	2712	2709B	2708B	2707B	2706B	2705B	2704C	2703C
Ranging	Auto/Manual	Auto/Manual	Auto/Manual	Manual	Manual	Auto/Manual	Manual	Manual
True RMS	AC + DC	√	√	√	-	-	-	-
Current	10 A AC/DC	10 A AC/DC	10 A AC/DC	10 A AC/DC	200 mA AC/DC	10 A AC/DC	10 A AC/DC	10 A DC
Capacitance	to 40 uF	to 66 mF	-	to 20 uF	to 20 mF	-	to 20 uF	-
Transistor Test	-	-	-	√	-	-	√	-
Frequency Counter	to 500 kHz	to 66 MHz	-	to 20 MHz	to 40 kHz	-	to 20 MHz	-
Temperature	-	-	-	-	√	-	-	-
Logic Probe	-	-	-	√	-	-	√	-
Backlight LCD	√	√	-	-	√	-	-	-
Analog Bar Graph	√	-	√	-	-	-	-	-
Battery Test	-	-	-	-	-	-	-	√
Auto Power off	√	√	√	-	√	√	-	-